## **POWER MIXERS**

# MP 350 Turbo VV



Α

#### SALES DESCRIPTION

Ideal for blending soups and puréeing fruit and vegetables. Special institutional catering model intended for intensive use


B


#### **TECHNICAL DESCRIPTION**

MP 350 Turbo VV Power Mixer. 120V/60/1. Power: 1 HP/660 W. Variable speed: 3,000 to 10,000 rpm. 100% stainless-steel blades, bell and shaft (total length: 14"). "Easy Plug" system featuring detachable power cord

C TECHNICAL CHARACTERISTICS	
Effective output	1 HP/600W
Electrical data	120V/60/1 2.3 A – plug supplied
Variable speed	3,000 to 10,000 rpm
Recyclability	95%
Net weight	15 lbs
Reference	MP350 Turbo VV

# robot Ø coupe°





### CHARACTERISTICS AND BENEFITS

#### MOTOR UNIT

E

D

- Power 1 HP/600W
- Stainless-steel motor unit with air vents in the top section to ensure watertightness
- Ridge on motor housing serves as a rest and pivot on the pan rim for greater user comfort
- Variable speed: 3,000 to 10,000 rpm
- Self-regulating speed system
- New patented "Easy Plug" system making it easier to replace the power cord during after-sales servicing
- Cord winding system for tidy storage and optimum lifespan
- Indicator light to check if the power cord is properly connected

#### SHAFT AND BELL

- 100% stainless-steel blades, bell and shaft (total length: 14").
- Foot with detachable bell and blades (patented system) exclusive to Robot-Coupe) for optimum sanitation.
- Watertight bell design for optimum lifespan

### STANDARD ATTACHMENTS

- Wall-mounted power Mixer holder
- Tool for attaching and detaching the blades

### **STANDARDS**

ETL electrical and sanitation Listed/ cETL (Canada)



Specification sheet

www.robotcoupeusa.com

Update : November 2018

Robot Coupe USA, Inc. 264 South Perkins - Ridgeland, MS 39157 PH: 601-898-8411 - Toll free: 800-824-1646 - Fax: 601-898-9134 info@robotcoupeusa.com

# MP 350 Turbo VV

robot @ coupe°



G

120V/60/1 – power cord and plug supplied

6 15/1

ĺΛ.



(A)

**DRAWINGS & DIMENSIONS** 

7<u>3/8</u>

28 35/64