

Product	
Model #	Quantity



# BOH Series Induction Flameless Cooking Slide-In Range Cabinet

#### **Models:**

SKU	RANGES	PRODUCT DIMENSIONS	SHIPPING DIMENSIONS*	WEIGHT	OPTIONS
BOH-1800	SM-181R x 4	36"W x 33.25"D x 36.03"H	37"W x 45"D x 39"H	266 lbs	N/A
BOH-1800D					Doors
BOH-2600	SM-261R x 4	36"W x 33.25"D x 36.03"H	37"W x 45"D x 39"H		N/A
BOH-2600D					Doors
BOH-3500C	SM-351R x 4	36"W x 33.25"D x 36.03"H	37"W x 45"D x 39"H		N/A
BOH-3500D					Doors
BOH-1800-6	SM-181R x 6	48"W x 33.25"D x 36.03"H	70"W x 40"D x 60"H	500 lbs	N/A
BOH-1800D-6					Doors
BOH-2600-6	SM-261R x 6	48"W x 33.25"D x 36.03"H	70"W x 40"D x 60"H		N/A
BOH-2600D-6					Doors
BOH-3500-6	SM-351R x 6	40  144   22 25  5   26 02  44	70//\\ 40//\\ 60//\\		N/A
BOH-3500D-6		48"W x 33.25"D x 36.03"H	70"W x 40"D x 60"H		Doors

<sup>\*</sup> Estimated crate dimensions, crates are built to size. Sizes may vary.

## **Description:**

Optimize your back-of-house operation with the power of induction – our BOH Series Flameless Cooking Slide-In Induction Range Cabinets offer cleaner, more efficient & safer cooking, prepping, and warming in a compact, stainless-steel cart designed for commercial settings.

## **Agency Listings:**

- FCC
- ETL
- ETL-Sanitation to NSF-4
- UL-197





### **Features:**

- 304 Stainless Steel Welded Construction
- 304 Series Stainless Steel Top & Exterior
- (1) Fix Mid Shelf
- Adjustable Equipment Feet
- Durable, easy to clean stainless steel body
- Individually mounted controls in apron
- Knurled knob for better grip & control
- Durable, 5" stainless-steel backsplash
- Interior power management
- Optional stainless steel doors with pocket handles
- Made in the US of domestic and imported parts


## **Key Dimensions:**


#### 4-Zone





#### 6-Zone





# **Electric Requirements:**

Each BOH Series Flameless Cooking Slide-In Induction Range Cabinet comes with its own Power Management System, powering the entire unit with a single receptacle, eliminating the need for multiple receptacles at various voltages.

Power Management Details:

MODEL	WATTS	VOLTAGE	PHASE	HERTZ	AMPS	PLUG	SYSTEM
BOH-1800	1800 x4	110-120	1	60	15	NEMA 14-50P	PM-2251
BOH-1800D							
BOH-1800-6							
BOH-1800D-6							
BOH-2600	2600 x4	208-240	1	60	15	NEMA 14-50P	PM-2221
BOH-2600D							
BOH-2600-6	2000 X4	200-240	1				
BOH-2600D-6							
BOH-3500	3500 x4	208-240 1		50-60	16.8	NEMA 14-50P x2	PM-2251 x2
BOH-3500D			1				
BOH-3500-6			1				
BOH-3500D-6							